



## OP-88296

Loose wires/M12 adapter

\*Please note that accessories depicted in the image are for illustrative purposes only and may not be included with the product.

## **Specifications**

Model	OP-88296
Туре	Loose wires/M12 adapter
Applicable product	FD-XA1/XA5 cables, or cables with cross sectional area 0.14 to 0.34 mm <sup>2</sup> and outer diameter ø 3.5 to 6 mm 0.14 " to 0.24 "
Frequency of connections between conductors of the same cross section	10
Insertion/withdrawal cycles	More than 100 times
Wire diameter including insulation	ø 0.7 to 1.6 mm 0.028 " to 0.06 "
enclosure rating	IP65/67
Ambient temperature	-25 °C to +80 °C -13 to 176 °F
Note	A connector that converts loose wires to a M12 4-pin connector. Useful for connecting to IO-Link compatible master units.
Weight	Approx. 12 g



## **Dimensions**

\* Download CAD file or product manual for larger image/text and more detail.



